



Sustainiac® STEALTH PLUS
sustainer
Shredder installation, with
toggle pickup switches
11/00

KEEP WIRES AS SHORT AS POSSIBLE.

9V BATTERY
(can fit under upside-down jack-plate)

PICKUP SELECTOR SWITCHES

CAUTION: Do not solder ground wire to switch body of combination potentiometer/switches. Solder to potentiometer section. Switches have plastic parts inside which will melt!

POTENTIOMETER
Solder ground connection here. First, file off plating.

not here

SWITCH

- Make sure all ground connections are made.
- 1-output jack
 - 1-bridge or tremolo
 - 2-pickups
 - 1-driver shield.
 - 1-tone capacitor
 - 1-ON/OFF switch
 - 1-battery
 - 1-10 pin connector
 - 1-8 pin connector
 - 3-pots bodies (not switch bodies)
- TOTAL = 13ground**

GROUND
bridge pu. shield and ground wire to a pot body.

Note: Only bridge pickup and Stealth circuit board connected to this switch

To tremolo spring bracket

OUTPUT JACK

twist together and keep away from pickup signal wires

Connect tone pot to volume pot with shielded cable as shown. Connect only one end of shield to ground.

MASTER TONE POT & ON/OFF SWITCH