

SUSTAINIAC STEALTH PRO INSTALLATION  
 3-PICKUP GUITAR  
 7-08

- NOTES:**
1. Make sure that battery (-) wire and black wire of 10-pin connector go to same ground connection.
  2. Make sure that all pot bodies are connected to ground and also to output jack shield terminal.
  3. Use a shielded wire for the output signal, or keep it physically away from orange/blue/white Sustainiac wires, to avoid static electricity damage to circuit.
  4. Orient board to place 8-pin connector close to pickup selector.
  5. Bridge, middle pickup ground and shield wires not shown. These connect to ground (pot body)

