

Sustainiac® STEALTH PRO Ibanez JS® installation With AUX-JS board

August, 2016

← neck

Splice 2 blue wires together.
Cover with heatshrink tubing.

IBANEZ OUTPUT JACK

Sustainiac shielded driver wire

Sustainiac circuit board

10-pin

8-pin

Drive pot

VIOLET/GRAY PAIR

WHITE

wht
blk

Tone capacitor

push-pull
Sustainiac ON/OFF
and Tone control

2-pin connectors

AUX-JS board

8-pin connector

red
blk
blk
blk
blk
blk
blk
blk

VIO
GRY

Toggle
Harmonic Mode
control switch

Twist violet/gray of
8-pin. and keep away
from guitar signal wires.

BARREL TYPE
THREADED BODY

330pF
cap

Bridge pickup wire

Pickup selector

ORANGE

VOLUME/
330 pF cap

Battery wires

